Digital 382



Article

Item no.	Description
122421	**Digital 382** 2-channel mini hand transmitter, unidirectional, 433 MHz Multi-Bit

Scope of delivery

- Hand transmitter with battery
- Wall bracket with installation material
- Coding plug

Features

Features

- 2 function keys for free assignment
- Signaling by red LED
- Eyelet for attachment to keychain or lanyard
- Simple and direct copying of a hand transmitter key to another hand transmitter by means of plug-in contacts

Use

- For all Marantec controls and third-party products (in conjunction with corresponding Multi-Bit receiver)

Technical data

- Housing type: Mini
- Number of freely programmable keys: 2
- Channels: 2
- Antenna: Integrated
- Radio frequency: 433 MHz
- Radio technology: Multi-Bit
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: RAL 7011
- Temperature (min.) [°C]: -20
- Temperature (max.) [°C]: 60
- Temperature (min./max.) [°C]: -20/60
- Temperature (min.) [°F]: -4
- Temperature (max.) [°F]: 140
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 39
- Height [mm]: 86
- Depth [mm]: 12
- Weight [kg]: 0.02
- Packing width: 56
- Packing height: 52
- Packing depth/length: 101
- Packing weight: 0.06
- Freight forwarding articles: No
- GTIN: 4062434003817
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

Accessories

Item no.	Description
167535	**Sun visor clip** for Mini Hand Transmitters Digital 564, 663, 382, and 384, 10 pieces à
140224	**Wall mount mini** for mini hand transmitters Digital 564, 663, 382 and 384, 5 pieces

Predecessors

Item no.	Description	Discontinuation
123539	**Digital 382 (MFZ)** 2-channel mini hand transmitter, unidirectional, 433 MHz Multi-Bit, MFZ coding (only compatible with identical RCLXX, RCUXX and CS radio hand transmitters and receivers with MFZ coding)	