

# Digital 382



## Article

---

| Item no. | Description                                                                           |
|----------|---------------------------------------------------------------------------------------|
| 122419   | <b>Digital 382</b> 2-channel mini hand transmitter, unidirectional, 868 MHz Multi-Bit |

## Scope of delivery

---

- Hand transmitter with battery
- Wall bracket with installation material
- Coding plug

## Features

---

### Features

- 2 function keys for free assignment
- Signaling by red LED
- Eyelet for attachment to keychain or lanyard
- Simple and direct copying of a hand transmitter key to another hand transmitter by means of plug-in contacts

## Use

---

- For all Marantec controls and third-party products (in conjunction with corresponding Multi-Bit receiver)

## Technical data

---

- Housing type: Mini
- Number of freely programmable keys: 2
- Channels: 2
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: Multi-Bit
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: RAL 7011 RAL 7016
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 39
- Height [mm]: 86
- Depth [mm]: 12
- Weight [kg]: 0.02
- Packing width: 56
- Packing height: 52
- Packing depth/length: 101
- Packing weight: 0.066
- Freight forwarding articles: No
- GTIN: 4062434003800
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

## Accessories

---

| Item no. | Description                                                                               |
|----------|-------------------------------------------------------------------------------------------|
| 140224   | <b>Wall mount mini</b> for mini hand transmitters Digital 564, 663, 382 and 384, 5 pieces |

## Predecessors

---

| Item no. | Description              | Discontinuation |
|----------|--------------------------|-----------------|
| 123585   | <b>Digital 382 (MFZ)</b> | 2023-06-12      |

| Item no. | Description                                                                                      | Discontinuation |
|----------|--------------------------------------------------------------------------------------------------|-----------------|
| 160380   | <b>Digital 382</b> 2-channel mini hand transmitter, unidirectional, 868 MHz Multi-Bit, set of 10 | 2024-01-19      |
| 160387   | <b>Digital 382</b> 2-channel mini hand transmitter, unidirectional, 868 MHz Multi-Bit, set of 25 | 2024-01-19      |
| 160394   | <b>Digital 382</b> 2-channel mini hand transmitter, unidirectional, 868 MHz Multi-Bit, set of 50 | 2024-01-19      |