

# Digital 713



## Article

---

| Item no. | Description  |
|----------|--|
| 165748   | <b>Digital 713</b> 2-channel universal receiver with 2,000 memory locations and 2 relays, 24 V, IP20, unidirectional, 868 MHz DM7S |

## Scope of delivery

---

- Mini universal receiver with memory module
- 2 Velcro adhesive pads

## Features

---

### Features

- 2 channels for free assignment
- 2 potential-free relay contacts for switching electrical devices, e.g. impulse input of a gate control system
- IMPULSE, ON/OFF or timer function (1 to 1,000 seconds) separately adjustable for each channel
- Control of additional electrical consumers, e.g. light
- Pluggable memory module for up to 2,000 hand transmitters
- Programming of the memory module is done with the help of the programmer and the computer software
- Compact size

## Use

---

- For all Marantec controllers and third-party products

## Technical data

---

- Channels: 2
- Number of memory locations: 2,000
- Antenna: Wire antenna
- Radio frequency: 868 MHz
- Radio technology: DM7S
- Radio coding: Marantec
- Communication direction: Unidirectional
- Connection type: Conventional
- Contact type: 2 CO
- Outputs:  
2 potential-free relay contacts (CO)
- Protection class: IP20
- Color: Black
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- Operating voltage [V]: 24 V-AC 24 V-DC
- Operating voltage type: Direct current
- Rated current [A]: 0.05
- Contact load (max.):  
24 V-DC/0.5 A
- Width [mm]: 102
- Height [mm]: 45
- Depth [mm]: 20
- Packing width: 87
- Packing height: 38
- Packing depth/length: 147
- Packing weight: 0.063
- Freight forwarding articles: No
- GTIN: 4062434019856
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

## Accessories

---

| Item no. | Description  |
|----------|--|
| 102957   | <b>Magnetic foot antenna</b> Magnetic foot antenna with 5 m cable, conventional, 868 MHz |
| 160904   | <b>Digital 720</b> USB programmer for DM7S transmitter and receiver                      |