

Digital 706



Article

Item no.	Description
187994	Digital 706 10-channel maxi hand transmitter, unidirectional, 868 MHz DM7S, set of 50

Scope of delivery

- 50 hand transmitters with battery

Features

Features

- 10 function keys for free assignment
- Signaling by red LED
- High security through 128-bit AES-encrypted radio transmission and constantly changing radio code (rolling code method)
- Easy and fast programming of a large number of hand transmitters

Use

- For all Marantec controllers and other makes (in conjunction with corresponding DM7S receiver). Digital 711/712 receivers are compatible from R01 and Digital 713 is compatible from R00. DM7S software is compatible as of version 3.2.6

Technical data

- Housing type: Maxi
- Number of freely programmable keys: 10
- Channels: 10
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: DM7S
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: RAL 9005
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 39
- Height [mm]: 112
- Depth [mm]: 17
- Weight [kg]: 0.0000
- Packing width: 209
- Packing height: 140
- Packing depth/length: 270
- Packing weight: 2.194
- Freight forwarding articles: No
- GTIN: 4062434015650
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years