

# Digital 317



## Article

---

Item no.	Description
88990	<b>Digital 317</b> 999-channel multi-hand transmitter, unidirectional, 868 MHz Multi-Bit

## Scope of delivery

---

- Hand transmitter with battery
- Coding cable

## Features

---

### Features

- 999 channels for free assignment
- Operation by entering the channel number and pressing the enter key (IMPULSE)
- Indication by LC display
- Simple and direct copying of a hand transmitter key to another hand transmitter by means of plug-in contacts

## Use

---

- For all Marantec controls and third-party products (in conjunction with corresponding Multi-Bit receiver)

## Technical data

---

- Housing type: Maxi
- Number of freely programmable keys: 999
- Channels: 999
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: Multi-Bit
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: LY7P (metallic titanium gray)
- Temperature (min.)[°C]: 0
- Temperature (max.)[°C]: 50
- Temperature (min./max.)[°C]: 0/50
- Temperature (min.)[°F]: 32
- Temperature (max.)[°F]: 122
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 60
- Height [mm]: 150
- Depth [mm]: 22
- Weight [kg]: 0.11
- Packing width: 79
- Packing height: 45
- Packing depth/length: 196
- Packing weight: 0.154
- Freight forwarding articles: No
- GTIN: 4062434000441
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

## Accessories

---

Item no.	Description
72819	<b>Wall mount multi</b> for Digital 517, 518, 317 and 318 multi-hand transmitters

## Predecessors

---

Item no.	Description	Discontinuation
89154	<b>Digital 317</b>	2023-06-12