

Digital 517



Article

Item no.	Description
123052	Digital 517 999-channel multi-hand transmitter, unidirectional, 868 MHz bi.linked

Scope of delivery

- Hand transmitter with battery

Features

Features

- 999 channels for free assignment
- Operation by entering the channel number and pressing the enter key (IMPULSE)
- Indication by LC display
- High security through 128-bit AES-encrypted radio transmission and constantly changing radio code (rolling code method)

Use

- For all Marantec controls and third-party products (in conjunction with corresponding bi.linked receiver)

Technical data

- Housing type: Maxi
- Number of freely programmable keys: 999
- Channels: 999
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: bi.linked
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: LY7P (metallic titanium gray)
- Temperature (min.)[°C]: 0
- Temperature (max.)[°C]: 50
- Temperature (min./max.)[°C]: 0/50
- Temperature (min.)[°F]: 32
- Temperature (max.)[°F]: 122
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 60
- Height [mm]: 150
- Depth [mm]: 22
- Weight [kg]: 0.11
- Packing width: 79
- Packing height: 45
- Packing depth/length: 197
- Packing weight: 0.136
- Freight forwarding articles: No
- GTIN: 4062434004104
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

Accessories

Item no.	Description
72819	Wall mount multi for Digital 517, 518, 317 and 318 multi-hand transmitters