

# Command 231



# **Article**

Item no.

Description

69533

**Command 231** 4-channel radio code push button with 3 permanent PINs, one temporary PIN, one light button and one protection cover, unidirectional, 868 MHz Multi-Bit

# Scope of delivery

- Radio code push button with 2 batteries
- · Coding plug
- · Installation material

# **Features**

#### **Features**

- Operation by entering a 4-digit PIN
- 3 freely selectable user PINs for free assignment with functions
- 1 freely selectable temporary user PIN (can be used 3 times)
- 1 function key for free assignment
- · Signaling by red LED
- · Hinged cover protects the keypad from dirt

### Use

• For all Marantec controllers and third-party products (in conjunction with corresponding multi-bit receiver)



# Technical data

• Number of freely programmable keys: 1

• Number of permanent PIN codes: 3

• Number of temporary PIN codes: 1

· Channels: 4

· Antenna: Integrated

· Radio frequency: 868 MHz

· Radio technology: Multi-Bit

· Radio coding: Marantec

· Communication direction: Unidirectional

· Protection class: IP54

• Color: LY7P (metallic titanium gray)

• Temperature (min.) [°C]: -20

• Temperature (max.) [°C]: 60

• Temperature (min./max.) [°C]: -20/60

• Temperature (min.) [°F]: -4

• Temperature (max.)[°F]: 140

• battery type: CR2032, 3 V

Battery count: 2Width [mm]: 70

Height [mm]: 198

Height (min.)[mm]: 110

• Height (max.) [mm]: 198

• Height (min.-max.)[mm]: 110-198

• Depth[mm]: 48

• Packing width: 87

• Packing height: 72

• Packing depth/length: 125

• Packing weight: 0.244

· Freight forwarding articles: No

• GTIN: 4011805049985

Customs tariff number: 85269200Country of origin 1000: Deutschland

· Garantie: 2 years

# **Predecessors**

Item no.DescriptionDiscontinuation76250Command 2312023-06-12