

Digital 371 conversion set



Article

Item no.	Description
78073	Digital 371 conversion set consisting of Digital 371 EU (type F) and Digital 384, unidirectional, 868 MHz multi-bit

Scope of delivery

- Digital 371 socket receiver with type F earthed plug/socket and connecting cable, 1,500 mm
- Digital 384 Mini hand transmitter 4-channel with battery, wall bracket with mounting material and coding plug

Features

Digital 371

Features

- 1 channel for free assignment
- 1 potential-free relay contact for switching an electrical device, e.g. impulse input of a gate control system
- IMPULSE function
- Power supply via the mains socket of the operator without blocking it
- Easy conversion of third-party operators to Marantec hand transmitters or to change the radio frequency

Digital 384

Features

- 4 function keys for free assignment

- Signaling by red LED
- Eyelet for attachment to keychain or lanyard
- Simple and direct copying of a hand transmitter key to another hand transmitter by means of plug-in contacts

Use

Digital 371

- For all Marantec controllers and third-party products

Digital 384

- For all Marantec/MFZ controllers and third-party products (in conjunction with corresponding multi-bit receiver)

Technical data

Digital 371

- Channels: 1
- Number of memory locations: 1
- Antenna: Wire antenna
- Radio frequency: 868 MHz
- Radio technology: Multi-Bit
- Radio coding: Marantec
- Communication direction: Unidirectional
- Connection type: Pluggable
- Contact type: 1 NO
- Outputs:
 - 1 potential-free relay contact (NO)
- Protection class: IP20
- Color: RAL 9003
- Temperature (min.) [°C]: -10
- Temperature (max.) [°C]: 40
- Temperature (min./max.) [°C]: -10/40
- Temperature (min.) [°F]: 14
- Temperature (max.) [°F]: 104
- Operating voltage [V]: 230 V/1~
- Operating voltage type: Alternating current
- Rated current [A]: 0.03
- Power consumption [VA/W/kW]: 6.9 W
- Contact load (max.):
 - 24 V-DC/1A

- Width [mm]: 50
- Height [mm]: 120
- Depth [mm]: 75
- Packing width: 87
- Packing height: 87
- Packing depth/length: 132
- Packing weight: 0.224
- Freight forwarding articles: No
- GTIN: 4062434000120
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years

Digital 384

- Housing type: Mini
- Number of freely programmable keys: 4
- Channels: 4
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: Multi-Bit
- Radio coding: Marantec
- Communication direction: Unidirectional
- Color: RAL 7011 RAL 7016
- Temperature (min.) [°C]: -20
- Temperature (max.) [°C]: 60
- Temperature (min./max.) [°C]: -20/60
- Temperature (min.) [°F]: -4
- Temperature (max.) [°F]: 140
- battery type: CR2032, 3 V
- Battery count: 1
- Width [mm]: 39
- Height [mm]: 86
- Depth [mm]: 12
- Weight [kg]: 0.02
- Packing width: 56
- Packing height: 52
- Packing depth/length: 101
- Packing weight: 0.067
- Freight forwarding articles: No
- GTIN: 4062434003916
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years