

Command 131



Article

Item no.	Description
65694	Command 131 2-channel radio indoor push button with 2 inputs for key switch, unidirectional, 433 MHz Multi-Bit

Scope of delivery

- Radio interior push button with 2 batteries
- Coding cable
- Installation material

Features

Features

- 2 function keys for free assignment
- Connection with conventional wiring for external push buttons for direct switching of each function key
- Signaling by red LED
- Simple and direct copying of a hand transmitter key to another hand transmitter by means of plug-in contacts

Use

- For all Marantec controllers and third-party products (in conjunction with corresponding multi-bit receiver)

Technical data

- Number of freely programmable keys: 2
- Channels: 2
- Antenna: Integrated
- Radio frequency: 433 MHz
- Radio technology: Multi-Bit
- Radio coding: Marantec
- Communication direction: Unidirectional
- Inputs:
2 inputs for push buttons
- Push button type: Push button
- Protection class: IP20
- Color: RAL 7011 RAL 7016
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- battery type: CR2032, 3 V
- Battery count: 2
- Width [mm]: 80
- Height [mm]: 80
- Depth [mm]: 27
- Packing width: 90
- Packing height: 73
- Packing depth/length: 127
- Packing weight: 0.148
- Freight forwarding articles: No
- GTIN: 4062434000144
- Customs tariff number: 84719000
- Country of origin 1000: Deutschland
- Garantie: 2 years