

# Command 222



## Article

---

Item no.	Description
72873	<b>Command 222</b> 4-channel radio code switch with 3 permanent PINs, one temporary PIN and one light button, vandalism-proof, unidirectional, 868 MHz Multi-Bit

## Scope of delivery

---

- Radio code push button with battery
- Coding cable
- Installation material

## Features

---

### Features

- Operation by entering a 4-digit PIN
- 3 freely selectable user PINs for free assignment with functions
- 1 freely selectable temporary user PIN (can be used 3 times)
- 1 changeable master PIN for management
- 1 function key for free assignment
- Metal keys and security screw protect against vandalism

## Use

---

- For all Marantec controllers and third-party products (in conjunction with corresponding multi-bit receiver)

## Technical data

---

- Number of freely programmable keys: 1
- Number of permanent PIN codes: 3
- Number of temporary PIN codes: 1
- Channels: 4
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: Multi-Bit
- Radio coding: Marantec
- Communication direction: Unidirectional
- Protection class: IP65
- Color: RAL 9006
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- battery type: Block, 9 V
- Battery count: 1
- Width [mm]: 60
- Height [mm]: 142
- Depth [mm]: 30
- Packing width: 110
- Packing height: 90
- Packing depth/length: 180
- Packing weight: 0.465
- Freight forwarding articles: No
- GTIN: 4062434000199
- Customs tariff number: 84719000
- Country of origin 1000: Deutschland
- Garantie: 2 years