

Digital 645



Article

Item no.	Description
101144	Digital 645 2-channel radio indoor push button with status request and vacation function, bidirectional, 868 MHz bi.linked

Scope of delivery

- Radio interior push button with 2 batteries
- Installation material

Features

Features

- 2 function keys for free assignment
- 1 button for switching the vacation mode ON/OFF (deactivation of radio reception)
- 1 key for switching the operator lighting ON/OFF
- Integrated infrared motion detector for automatic switching of operator lighting
- Signaling by red LED
- High security through 128-bit AES-encrypted radio transmission and constantly changing radio code (rolling code method)

Use

- For all Marantec controllers and third-party products (in conjunction with corresponding bi.linked receiver)

Technical data

- Number of freely programmable keys: 2
- Number of pre-programmed keys: 2
- Channels: 5
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: bi.linked
- Radio coding: Marantec
- Communication direction: Unidirectional
- Inputs:
2 inputs for push buttons
- Push button type: Push button
- Sensoren: PIR
- Protection class: IP20
- Color: RAL 9005 RAL 9006
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- battery type: CR2032, 3 V
- Battery count: 2
- Width [mm]: 82
- Height [mm]: 83
- Depth [mm]: 26
- Packing width: 0
- Packing height: 0
- Packing depth/length: 0
- Packing weight: 0.135
- Freight forwarding articles: No
- GTIN: 4062434001004
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years