

# Digital 525



## Article

---

Item no.	Description
101149	<b>Digital 525</b> 4-channel radio code push button with 3 permanent PINs, one temporary PIN and one light button, unidirectional, 868 MHz bi.linked

## Scope of delivery

---

- Radio code push button with 2 batteries
- Installation material

## Features

---

### Features

- Operation by entering a 4-digit PIN
- 3 freely selectable user PINs for free assignment with functions
- 1 freely selectable temporary user PIN (can be used 3 times)
- 1 changeable master PIN for management
- 1 function key for free assignment
- Signaling by red LED
- High security through 128-bit AES-encrypted radio transmission and constantly changing radio code (rolling code method)

## Use

---

- For all Marantec controllers and third-party products (in conjunction with corresponding bi.linked receiver)

## Technical data

---

- Number of freely programmable keys: 1
- Number of permanent PIN codes: 3
- Number of temporary PIN codes: 1
- Channels: 4
- Antenna: Integrated
- Radio frequency: 868 MHz
- Radio technology: bi.linked
- Radio coding: Marantec
- Communication direction: Unidirectional
- Protection class: IP54
- Color: RAL 9006
- Temperature (min.)[°C]: -20
- Temperature (max.)[°C]: 60
- Temperature (min./max.)[°C]: -20/60
- Temperature (min.)[°F]: -4
- Temperature (max.)[°F]: 140
- battery type: AAA, 1.5 V
- Battery count: 2
- Width [mm]: 80
- Height [mm]: 102
- Depth [mm]: 35
- Packing width: 86
- Packing height: 72
- Packing depth/length: 124
- Packing weight: 0.207
- Freight forwarding articles: No
- GTIN: 4062434001028
- Customs tariff number: 85269200
- Country of origin 1000: Deutschland
- Garantie: 2 years